

## HDMI Signal Booster/Extender Cable, 1920x1200 at 60Hz/1080p (HDMI M/F), 1-ft.

MODEL NUMBER: **B123-001-60**



### Description

Tripp Lite's B123-001-60 HDMI Signal Extender increases the distance a 1080p @ 60Hz(or 1920 x 1200) signal can be transmitted beyond the recommended 16 ft.(5 m.). It supports computer video resolutions up to 1920 x 1200, and HD resolutions up to 1080p @ 60Hz, at a maximum distance of 125 ft. from the source. Use P568-Series HDMI cables in most applications. When extending a 1080p @ 60Hz(or 1920 x 1200) signal more than 75 ft., use cable made with 24Awg wiring, such as the [P568-100-HD](#).(Lengths over 100 ft. are available from Tripp Lite as a custom order) 24Awg HDMI cable is also needed when extending a 3D signal more than 50 ft.. A 3D signal can be extended up to 125 ft. using 24Awg HDMI cable. Simply connect the longer cable between the source and the B123-001-60, and the shorter cable(16 ft. or less) between the adapter and the monitor/TV. Software or drivers are not required. Built-in Equalization control to adjust the video image. HDCP compliant. Compliant with the Federal Trade Agreements Act(TAA) for GSA Schedule purchases.

### Features

- Extend a 1080p @ 60Hz(or 1920 x 1200) HDMI signal up to 125 ft. from the source
- Use P568-Series HDMI cables in most applications
- When extending a 1080p @ 60Hz(or 1920 x 1200) signal more than 75 ft., use cable made with 24Awg wiring, such as the [P568-100-HD](#).
- Lengths over 100 ft. are available from Tripp Lite as a custom order)
- 24Awg HDMI cable is also needed when extending a 3D signal more than 50 ft.. A 3D signal can be extended up to 125 ft. using 24Awg HDMI cable
- Supports DTS-HD, Dolby True HD and 7.1 Channel Surround Sound Audio
- Built-in Equalization control to adjust the video image
- HDCP compliant
- No software or drivers required
- Compliant with the Federal Trade Agreements Act(TAA) for GSA Schedule purchases

## Specifications

### Highlights

- Extend a 1080p @ 60Hz(or 1920 x 1200) HDMI signal up to 125 ft. from the source
- When extending a 1080p @ 60Hz(or 1920 x 1200) signal more than 75 ft., use cable made with 24Awg wiring, such as the [P568-100-HD](#)
- 24Awg HDMI cable is also needed when extending a 3D signal more than 50 ft.. A 3D signal can be extended up to 125 ft. using 24Awg HDMI cable
- Supports DTS-HD, Dolby True HD and 7.1 Channel Surround Sound Audio
- Compliant with the Federal Trade Agreements Act(TAA) for GSA Schedule purchases

### Package Includes

- B123-001-60 HDMI Active Extender
- External Power Supply with NEMA 1-15P Plug( Input: 100-240V, 50/60Hz, 0.5A Output: 5V, 2A )
- Screwdriver for Equalization adjustment



<b>OVERVIEW</b>	
Cable Type	HDMI
<b>INPUT</b>	
Cable Length (ft.)	1
Cable Length (m)	0.30
<b>CONNECTIONS</b>	
Connector A	HDMI (MALE)
Connector B	HDMI (FEMALE)
Number of Connectors	2
Ports	1
<b>SPECIAL FEATURES</b>	
Chromebook Compatible	Yes
<b>WARRANTY</b>	
Product Warranty Period (Worldwide)	1-year limited warranty

© 2015 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: <http://www.tripplite.com/products/product-certification-agencies>